



AC-15S

NON-CONTACT AC VOLTAGE TESTER PEN WITH LED FLASHLIGHT

- High power rear flashlight
- Thinner probe tip for working with wall outlets
- Green LED means power on, flashing red LED with beeper means voltage detected
- Vibration on Voltage detection
- Low battery self test & auto power off
- Two modes, green means high voltage mode, yellow means low voltage mode
- Forward facing flashlight
- Flash and Beep rate increase as the detector gets closer to the voltage source helping the user pinpoint live circuits
- Power ON/OFF switch & Silent Mode
- Pocket clip for easy storage
- CATIV-1000V , IP67 Water Proof & 2m Drop-proof



General Specifications

Voltage range	50 V AC to 1000 V AC & 200 V AV to 1000V AC (50/60Hz)	
Type	Non-Contact AC Voltage Detector	
Voltage Detection Indicators	Two modes, green means high voltage, yellow means low voltage Motor Shaking with Audible Discontinuous Beeping	
Operating conditions	Temperature	0°C to 40°C (32°F to 104°F)
	Relative Humidity	<80%
	Altitude	Up to 6,562 feet (2,000 meters) maximum
	Environment	Indoor Use
Power On Indication & Illuminator	Visual	High Intensity Green LED
	Audible	Continuous Beeping Sound
Power Off & Auto Power Off	Visual	Power-On LED turns off
	Audible	Continuous Beeping Sound
Low Battery Indicators	Visual	Green LED Blinks
	Audible	Series of Beeping Sounds
Batteries	Two "AAA"1.5V batteries	
Pollution Degree	2	

Safety Complies with EN 61010-1 2nd Edition, EN 61326 EMC to 1000 V CAT IV

Accessories

Battery, Instruction Manual.

Contact :

CEM INSTRUMENTS (INDIA) PVT. LTD.

32A, Ganesh Chandra Avenue, 4th Floor, Kolkata-700013

Tel: 033-22151376, 22159759

Email: info@cem-instruments.in

Web: www.cem-instruments.in

